

# V-TAC

Meaningful Innovation.

# Portable Power Station 1000W

- Ⓞ Upgrade to LiFePO4 battery capacity 1024Wh, 12 outlets
- Ⓞ AC230V fast charging, wide range solar charging voltage (12-100V 400W MAX)
- Ⓞ 2 x DC head 5521 output port and 1 x automobile auxiliary power outlet(total 12V/8A)
- Ⓞ Speed charger QC 3.0 Output x 2, TYPE-C : Output PD100W X2
- Ⓞ 3 x EU /BS standard AC ports, 1200W AC 230V Power Output
- Ⓞ LED Flashlight with SOS
- Ⓞ Quiet noise level during operation
- Ⓞ Over-current, Over-voltage , over-temperature and Short Circuit Protections 9, Cycle life: 2000 Cycles



V-TAC.EU | LED-EUROPE.PL



## LISTING DETAILS

Model:	<b>VT-1001N</b>
SKU Code:	<b>EU-Plug -11627   BS-Plug -11742</b>
EAN Code:	<b>EU-Plug- 3800170200098 BS-Plug -3800170203280</b>

## MASTER BOX PACKAGING

Qty:	<b>1pc/box</b>
Net Weight :	<b>16.5kgs</b>
Product Size :	<b>W*H*L 420*240*266mm</b>

## GENERAL DATA

<b>BATTERY</b>	Battery capacity	LiFePO4(IRF34189 25.6V 40Ah/1024Wh)	
	Cell model	IRF34189	
<b>DC/INPUT</b>	AC 230V Charging	230V 1000W max	
	XT60 Solar Charger	12-100V 10A 400W max Charger	
<b>USB/OUTPUT</b>	USB1 Output	QC 3.0 18W 5V3A/9V2A/12V1.5A	
	USB2 Output	QC 3.0 18W 5V3A/9V2A/12V1.5A	
	TYPE-C 1 Output	PD100W ,5V3A / 9V3A / 15V3A / 15V3A / 20V3A/20V 5A	
	TYPE-C2 Output	PD100W ,5V3A / 9V3A / 15V3A / 15V3A / 20V3A/20V 5A	
<b>DC OUTPUT</b>	DC 1 Output	12V/8A	100W shared
	DC 2 Output	12V/8A	
	Cigarette lighter Output	12V/8A	
<b>AC OUTPUT</b>	AC Output 1	AC Power Output 230V Sine WAVE 1200W PEAK 1800W	1200W shared
	AC Output 2	AC Power Output 230V Sine WAVE 1200W PEAK 1800W	
	AC Output 3	AC Power Output 230V Sine WAVE 1200W PEAK 1800W	
	Output Frequency max	Sine WAVE 1200W PEAK 1800W	
	Frequency	50Hz/60Hz	
<b>WIRELESS CHARGER</b>	DC	15W 5V 3A	
<b>LED LIGHTING</b>	Power	3W	
	Mode	High-Light/Low-light/SOS/Flash	

# 15W Wireless charger

